



Contribution ID: 192

Type: **Parallel session talk**

## Performances of EICROC0 ASIC to read-out pixelated AC-LGAD sensors for the Electron-Ion Collider (EIC)

Wednesday 8 October 2025 17:30 (20 minutes)

Finding the answers to the long-standing questions, such as, emergence of mass and spin of the proton from partons, saturation of gluon density, and gluon momentum distribution inside the proton and nuclei, motivated the EIC [1] under construction at Brookhaven National Laboratory, USA. The first EIC detector, ePIC (electron Proton-Ion Collision experiment), consists of a central barrel detector, as well as extensive beamline detectors in the outgoing electron (far-backward) and hadron (far-forward) beam directions. The far-forward (FF) detectors include Roman pots, which are placed inside vacuum and are intended to detect protons and ions scattered at very small angles ( $\sim 5$  mrad) in the forward direction, at  $\sim 30$  m downstream from the interaction point. The main goal of the FF detectors is to tag exclusive and diffractive events and to reconstruct their transverse momentum with a resolution of  $\sim 10$  MeV/c. This is obtained relying on a new generation of 4D tracking sensors, pixelated AC-LGADs (capacitively-coupled Low-Gain Avalanche Diode, pixel of  $500 \times 500 \mu\text{m}^2$ ) [2][3] capable of providing the required spatial (less than  $50 \mu\text{m}$  from charge sharing among neighboring pixels) and timing ( $\sim 30$  ps) resolutions. To read-out these novel LGADs exploiting their charge sharing capability, an optimized read-out large scale chip, EICROC ( $32 \times 32$  pads), is being designed at OMEGA. The first ASIC prototype, EICROC0\_v0 ( $4 \times 4$  pads) [5], is a system-on-chip with analog and digital processing including for each of the 16 channels a fast low-noise trans-impedance preamplifier, followed by two paths: a fast path with a discriminator connected to a 10-bit Time-to-Digital Converter (CEA/Irfu) for time measurement (ToA) with a 25 ps accuracy; and a slow path with shaper connected to an 8-bit 40 MHz successive approximation Analog-to-Digital Converter (AGH Krakow) providing amplitudes. The performance results obtained at IJCLab with pixelated AC-LGAD sensors read out by the EICROC0\_v0 ASIC, including preamplifier response and digital data from the TDC and ADC, will be presented. These results rely on measurements performed using the internal charge injection system, a beta source, and an infrared laser. Special emphasis will be placed on quantifying the charge-sharing ratio between adjacent pixels, together with evaluating the timing and spatial resolutions achievable with the EICROC0\_v0 ASIC

### Acknowledgement:

This work is benefitting from support from the French Agence Nationale de la Recherche (ANR), under grant ANR-24-CE31-5571 (project ROAD\_4\_EIC).

### References:

- [1] R. Abdul Khalek et al., “Science Requirements and Detector Concepts for the Electron-Ion Collider: EIC Yellow Report”, Nucl. Phys. A 1026 (2022).
- [2] G. Giacomini et al., “Fabrication and performance of AC-coupled LGADs”, JINST 14 (2019), P09004.
- [3] S. Kita et al., “Optimization of capacitively coupled Low Gain Avalanche Diode (AC-LGAD) sensors for precise time and spatial resolution”, NIM A 1048 (2023) 168009.
- [4] A. Verplancke et al., “EICROC: an ASIC to read-out the AC-LGAD sensors for the Electron-Ion Collider (EIC)”, contribution to the proceedings of the Topical Workshop on Electronics for Particle Physics, Sept. 30th –Oct. 04th, 2024, Glasgow, UK, JINST 20 C04014.

**Author:** MARCHAND, Dominique (Université Paris-Saclay, CNRS/IN2P3, IJCLab, Orsay 91405, France)

**Co-authors:** VERPLANCKE, Adrien (OMEGA, CNRS, École Polytechnique, Institut Polytechnique de Paris, Palaiseau 91120, France); TRICOLI, Alessandro (Brookhaven National Laboratory, 11973 Upton, NY, U.S.A.); JENTSCH, Alexander (Brookhaven National Laboratory, 11973 Upton, NY, U.S.A.); TORRENTO COELLO, Ana (Université Paris-Saclay, CNRS/IN2P3, IJCLab, Orsay 91405, France); SHARMA, Arzoo (Université Paris-Saclay, CNRS/IN2P3, IJCLab, Orsay 91405, France); IKBAL, Ashik (Kent State University, 44242 Kent, OH, U.S.A.); KY, Beng-Yun (Université Paris-Saclay, CNRS/IN2P3, IJCLab, Orsay 91405, France); DE LA TAILLE, Christophe (OMEGA, CNRS, École Polytechnique, Institut Polytechnique de Paris, Palaiseau 91120, France); THIENPONT, Damien (OMEGA, CNRS, École Polytechnique, Institut Polytechnique de Paris, Palaiseau 91120, France); BOUYJOU, Florent (Université Paris-Saclay, CEA, IRFU, Centre CEA Paris-Saclay, Gif-sur-Yvette 91191, France); DULUCQ, Frédéric (OMEGA, CNRS, École Polytechnique, Institut Polytechnique de Paris, Palaiseau 91120, France); D'AMEN, Gabriele (Brookhaven National Laboratory, 11973 Upton, NY, U.S.A.); GIACOMINI, Gabriele (Brookhaven National Laboratory, 11973 Upton, NY, U.S.A.); MORON, Jakub (AGH University of Science and Technology, al. Adama Mickiewicza, 30-059 Kraków, Poland); HARA, Kazuhiko (University of Tsukuba, 1-1-1 Tennodai, Tsukuba, 305-8571, Ibaraki, Japan); GUILLOSSOU-JNAID, Kinann (OMEGA, CNRS, École Polytechnique, Institut Polytechnique de Paris, Palaiseau 91120, France); NAKAMURA, Koji (High Energy Research Organization (KEK), 1-1 Oho, Tsukuba, 305-0801, Ibaraki, Japan); SERIN, Laurent (Université Paris-Saclay, CNRS/IN2P3, IJCLab, Orsay 91405, France); IDZIK, Michal (AGH University of Science and Technology, al. Adama Mickiewicza, 30-059 Kraków, Poland); SEGUIN-MOREAU, Nathalie (OMEGA, CNRS, École Polytechnique, Institut Polytechnique de Paris, Palaiseau 91120, France); BRAND-FOISSAC, Olivier (Université Paris-Saclay, CNRS/IN2P3, IJCLab, Orsay 91405, France); SHANMUGANATHAN, Prashanth (Brookhaven National Laboratory, 11973 Upton, NY, U.S.A.); TRIBEDY, Prithwish (Brookhaven National Laboratory, 11973 Upton, NY, U.S.A.); KITA, Sayuka (University of Tsukuba, 1-1-1 Tennodai, Tsukuba, 305-8571, Ibaraki, Japan); CONFORTI, Selma (OMEGA, CNRS, École Polytechnique, Institut Polytechnique de Paris, Palaiseau 91120, France); PAUL, Souvik (Stony Brook University, 100 Nicolls Rd, Stony Brook, NY 11794, U.S.A.); EXTIER, Sébastien (OMEGA, CNRS, École Polytechnique, Institut Polytechnique de Paris, Palaiseau 91120, France); CORNET, Thomas (Université Paris-Saclay, CNRS/IN2P3, IJCLab, Orsay 91405, France); IMAMURA, Tomoka (University of Tsukuba, 1-1-1 Tennodai, Tsukuba, 305-8571, Ibaraki, Japan); CHAUMAT, Vincent (Université Paris-Saclay, CNRS/IN2P3, IJCLab, Orsay 91405, France); CHEN, Wei (Brookhaven National Laboratory, 11973 Upton, NY, U.S.A.)

**Presenter:** MARCHAND, Dominique (Université Paris-Saclay, CNRS/IN2P3, IJCLab, Orsay 91405, France)

**Session Classification:** SHARED SESSION

**Track Classification:** RDC 3 Solid State Tracking